

LED Outdoor Luminaires Eseta[™] wall sconce With Emergency Battery Pack

Installation Guide



This procedure is designed as an installation aid. Skilled trades people that are familiar with general construction and electrical installation techniques should perform the installation. Licensed electricians should provide electrical installation connections. Installations and connections should be done in accordance with all national and local codes and permits. In no way is this document intended to construe warranty or fitness of use of the products described, nor is it intended to provide safety instruction for those installing the product.

WARNING

IMPORTANT SAFEGUARDS

When using electrical equipment, basic safety precautions should always be followed including the following:

READ AND FOLLOW ALL SAFETY INSTRUCTIONS.

- Do not mount near gas or electric heaters
- Equipment should be mounted in location and at heights where it will not be subjected to tampering by unauthorized personnel.
- The use of accessory equipment not recommended by the manufacturer may cause an unsafe condition
- Do not use the equipment for other than its intended use.

SAVE THESE INSTRUCTIONS

Before proceeding with installation or service maintenance of this product:

- Disconnect power to reduce electrical shock risk.
- Review the entire Installation Guide.
- Inspect this properly packaged product for any damage that may have occurred during transit.
- Verify product application complies with manufacturer design recommendations.
- Verify the availability of necessary tools and incidental material.
- Verify applicable code requirements. Field assembly and installation are subject to acceptance by local inspection authority.
- Appropriate safety equipment to be determined by end user, per applicable safety standards and precautions.


Mounting – Surface/Direct Mount




Step 1 – Remove two screws **A** on the bottom of Eseta and remove mounting bracket on the back of the luminaire.



Step 2 – Place mounting bracket **B** on the wall (follow the arrow direction on the bracket). Secure mounting bracket with four screws.




Step 3 – Hang Eseta **C** on the mounting bracket.



Step 4 – Connect wiring to customer supplied junction box **D**. Connect the black wire to hot wire, connect the white wire to the neutral, connect the red wire¹ with ON/OFF switch wire, and connect the green wire to the ground.

1. Red wire is not supplied with any ordering option with PC.



Step 5 – Mount the luminaire on the bracket and secure Eseta with two screws **E** on the bottom of Eseta to complete the installation.