

GreenCobra GC1 & GC2 to GreenCobra J-Series Crossover Chart

This chart is intended to assist you in crossing over GC1/2 NW/CW products to our newer, more advanced, and more cost effective GCJ, CCL, and GCM J series product families. Please refer to the footnotes for important details.

GreenCobra GC1 & GC2						GreenCobra J-Series					
Product	LED Code	Current Code	Wattage	Lumens	Efficacy	Product	LED Code	Output Code	Wattage	Lumens	Efficacy
GC1-20F-350	20F	350	25	2700	108	GCJ1-30J-MV-40K-X-CC-025	30J	025	17	2669	157
GC1-20F-530	20F	530	35	3650	104	GCJ1-30J-MV-40K-X-CC-045	30J	045	27	4299	161
GC1-20F-700	20F	700	47	4800	102	GCJ1-30J-MV-40K-X-CC-050	30J	050	30	4830	161
GC1-30F-350	30F	350	35	3800	109	GCJ1-30J-MV-40K-X-CC-045	30J	045	27	4299	161
GC1-30F-530	30F	530	53	5400	102	GCJ1-30J-MV-40K-X-CC-055	30J	055	34	5532	163
GC1-30F-700	30F	700	70	7000	100	GCJ2-30J-MV-40K-X-CC-070	30J	070	44	6864	156
GC1-40F-350	40F	350	45	5050	112	GCJ1-30J-MV-40K-X-CC-055	30J	055	34	5532	163
GC1-40F-530	40F	530	70	7200	103	GCJ3-30J-MV-40K-X-CC-075	30J	075	49	7256	149
GC1-40F-700	40F	700	92	9300	101	GCJ3-30J-MV-40K-X-CC-090	30J	090	64	9216	144
GC1-40F-1A	40F	1A	132	12300	93	GCM1-60J-MV-40K-X-CC-080	60J	080	80	12746	160
GC1-60F-350	60F	350	70	7600	109	GCJ3-30J-MV-40K-X-CC-080	30J	080	54	7992	148
GC1-60F-530	60F	530	101	10400	103	GCM1-60J-MV-40K-X-CC-105	60J	105	65	10525	162
GC1-60F-700	60F	700	133	13400	101	GCM1-60J-MV-40K-X-CC-135	60J	135	85	13402	158
GC1-80F-350	80F	350	85	9500	112	GCM1-60J-MV-40K-X-CC-095	60J	095	67	9648	144
GC1-80F-530	80F	530	133	14200	107	GCM2-60J-MV-40K-X-CC-140	60J	140	89	13884	156
GC1-80F-700	80F	700	180	17700	98	GCM3-60J-MV-40K-X-CC-185	60J	185	111	18327	149
GC2-80F-1A	80F	1A	277	24500	88	GCL1-80J-MV-40K-X-CC-255	80J	255	171	25504	149
GC2-90F-350	90F	350	95	10800	114	GCM1-60J-MV-40K-X-CC-105	60J	105	65	10525	162
GC2-90F-530	90F	530	150	16050	107	GCM3-60J-MV-40K-X-CC-170	60J	170	111	16872	152
GC2-90F-700	90F	700	195	19800	102	GCL1-80J-MV-40K-X-CC-205	80J	205	132	20350	154
GC2-100F-350	100F	350	105	11700	111	GCM1-60J-MV-40K-X-CC-115	60J	115	72	11574	161
GC2-100F-530	100F	530	167	17400	104	GCM1-60J-MV-40K-X-CC-080	60J	080	123	18327	149
GC2-100F-700	100F	700	220	22000	100	GCL1-80J-MV-40K-X-CC-220	80J	220	146	22216	152
GC2-120F-350	120F	350	130	14600	112	GCM2-60J-MV-40K-X-CC-140	60J	140	100	15400	154
GC2-120F-530	120F	530	200	20800	104	GCL1-80J-MV-40K-X-CC-205	80J	205	132	20350	154
GC2-120F-700	120F	700	260	26400	102	GCL1-80J-MV-40K-X-CC-265	80J	265	183	26444	145

NOTES:

- Applications previously served by GC1/2 products can now be served by lower cost and typically higher performing GCJ, GCL, and GCM products.
- Before making a final decision it is very important that you verify that the alternative product meets all your requirements.
- GC1/2 products are still available, however the alternative products provide better value and are therefore better suited for most applications.