

GreenCobra® H & G-Series Cross Over GreenCobra® J-Series for 4000K

GC H & G-SERIES						GC J-SERIES					
Product	LED Code	Current Code	Wattage	Lumens	Efficacy	Product	LED Code	Output Code	Wattage	Lumens	Efficacy
GCJ0	15H	300	15	2000	133	GCJ1	30J	025	17	2669	157
GCJ0	15H	390	19	2490	131	GCJ1	30J	025	17	2669	157
GCJ0	15H	490	24	3070	128	GCJ1	30J	025	17	2669	157
GCJ0	15H	490	24	3070	128	GCJ1	30J	045	27	4299	161
GCJ0	15H	590	30	3650	122	GCJ1	30J	045	27	4299	161
GCJ0	15H	700	35	4180	119	GCJ1	30J	045	27	4299	161
GCJ1	20H	350	25	3240	130	GCJ1	30J	025	17	2669	157
GCJ1	20H	350	25	3240	130	GCJ1	30J	045	27	4299	161
GCJ1	20H	450	29	3720	128	GCJ1	30J	045	27	4299	161
GCJ1	20H	530	34	4320	127	GCJ1	30J	045	27	4299	159
GCJ1	20H	580	39	4850	124	GCJ1	30J	050	30	4830	161
GCJ1	20H	700	46	5510	120	GCJ1	30J	055	34	5532	163
GCJ2	20H	700	45	5430	121	GCJ1	30J	055	34	5532	163
GCJ2	20H	830	54	6210	115	GCJ2	30J	060	37	5883	159
GCJ2	20H	830	54	6210	115	GCJ2	30J	070	44	6864	156
GCJ2	20H	900	58	6630	114	GCJ2	30J	070	44	6864	156
GCJ2	20H	1A	68	7430	109	GCJ3	30J	075	49	7256	149
GCM2	30H	530	48	6330	132	GCJ2	30J	070	44	6864	156
GCM2	30H	610	58	7440	128	GCJ3	30J	075	49	7256	148
GCM2	30H	700	68	8550	126	GCJ3	30J	085	58	8468	146
GCM2	30H	850	82	9830	120	GCJ3	30J	095	67	9648	144
GCM2	30H	1A	101	11720	116	GCM1	60J	115	72	11574	161
GCM2	40H	575	73	9590	131	GCJ3	30J	095	67	9648	144
GCM2	40H	700	88	11260	128	GCM1	60J	115	72	11574	161
GCM2	40H	850	107	13270	124	GCM1	60J	135	85	13402	158
GCM2	40H	950	121	14390	119	GCM2	60J	155	100	15400	154
GCM2	40H	1A	135	15430	114	GCM2	60J	155	100	15400	154
GCL1	60G	350	70	9250	133	GCJ3	30J	90	64	9216	144
GCL1	60G	450	85	11000	129	GCM1	60J	115	72	11574	161
GCL1	60G	530	105	13300	127	GCM1	60J	135	85	13402	158
GCL1	60G	610	120	15000	125	GCM2	60J	155	100	15400	154
GCL1	60G	700	135	16400	122	GCM3	60J	170	111	16872	152
GCL1	80G	350	85	11700	138	GCM1	60J	115	72	11574	161
GCL1	80G	450	115	15200	132	GCM2	60J	155	100	15400	154
GCL1	80G	530	130	16800	129	GCM3	60J	170	111	16872	152
GCL1	80G	610	160	20000	125	GCL1	80J	205	132	20350	154
GCL1	80G	700	185	22100	119	GCL1	80J	220	146	22216	152

NOTES:

- Cross-overs are based on the closest lumen output. Before substituting you should always compare the specification sheets of the original and suggested product as they are not identical.

(Continued on next page.)

GreenCobra® H & G-Series Cross Over GreenCobra® J-Series for 4000K (Continued)

GC H&G-SERIES						GC J-SERIES					
Product	LED Code	Current Code	Wattage	Lumens	Efficacy	Product	LED Code	Output Code	Wattage	Lumens	Efficacy
GCL2	60G	750	149	18500	124	GCM3	60J	185	123	18327	149
GCL2	60G	800	163	19600	120	GCL1	80J	205	132	20350	154
GCL2	60G	900	183	21200	116	GCL1	80J	220	146	22216	152
GCL2	60G	975	192	21800	114	GCL1	80J	220	146	22216	152
GCL2	60G	1A	208	22900	110	GCL1	80J	230	153	23129	151
GC2	96G	350	106	14600	138	GCM2	60J	155	100	15400	154
GC2	96G	450	130	17600	135	GCM3	60J	185	123	18387	149
GC2	96G	530	159	21100	133	GCL1	80J	220	171	22216	130
GC2	96G	610	180	23400	130	GCL1	80J	230	153	23129	151
GC2	96G	700	209	26700	128	GCL2	80J	265	183	26444	145
GC2	96G	750	226	28300	125	GCL2	80J	295	206	29252	142
GC2	96G	800	242	29800	123	GCL2	80J	295	206	29252	142
GC2	96G	900	273	32700	120	N/A					
GC2	96G	975	289	34100	118	N/A					
GC2	96G	1A	310	35800	115	N/A					

NOTES:

- Cross-overs are based on the closest lumen output. Before substituting you should always compare the specification sheets of the original and suggested product as they are not identical.